


Панель Knob SR-KN9001K2-UP White (KNX, DIM)



The SR-KN9001K2 is a wall mounted push button KNX dimmer controller with switch and dimming functions to control single color LED lighting. The KNX dimmer is designed with humanization LED indicator to show working status. It is compatible with SR-KNX9501 and SR-KNX9502 series KNX receivers and powered by KNX bus and consumes less than 12mA power. The KNX dimmer can offer gradually switching function, calling and storing scene function and shutter function. It is easy to mount the dimmer switch by 3M sticker on the wall.

KEY FEATURES:

- Gradually switching function
- LED indicator
- Calling and storing scene function
- Switching and dimming function
- Shutter function
- Multiple operating functions
- Operation voltage: 21-30V through KNX Bus
- Operation current: <12mA
- Dimension(mm): 55.5*55.5*13

REMOTE:

Part No.	Operation Voltage	Operation Current	Dimension (mm)	Remarks
SR-KN9001K2-UP	21-30VDC through KNX bus	<12mA	55.5*55.5*13	/

COMPATIBLE RECEIVER:

Part No.	Input Voltage	Output Current	Output Power	Output type	Dimension (mm)
SR-KNX9502FA	12-36VDC	4CH, 5A/CH	240-720W	Constant Voltage	53.4*166*23
SR-KNX9502FA3	12-36VDC	4CH, 0.35A/CH	16.8-50.4W	Constant Current	53.4*166*23
SR-KNX9502FA7	12-36VDC	4CH, 0.7A/CH	33.6-100.8W	Constant Current	53.4*166*23

RECEIVER WIRING DIAGRAM:

